

Microphone stand with fully programmable membrane switch, giving the option between push to talk, push to mute or latching without the need to change dip switches. Fitted with Mini XLR connector input to accommodate slim line Series microphones and LED indicator to identify microphone status.


SPECIFICATIONS

Switching: Touch Pad Fully Programmable for PTT, PTM & Latching

Indication: Red LED

Input: 3Pin Mini XLR with built in Phantom Power Module.
 PIN 1 = Phase -
 PIN 2 = Phase +
 PIN 3 = Ground

Output: 5Pin XLR
 PIN 1 = Ground
 PIN 2 = Control Input (activated in program 4 option 2)
 PIN 3 = PHASE -
 PIN 4 = Switch Out (Logic low when switch pressed)
 PIN 5 = PHASE +

Power Requirements: 48V Phantom Power

Finish: Satin black

Options: Microphones: C3100 C310-R C312-SR C313-SR C314-SR

Dimensions: Length Width Height
 120mm 100mm 32mm
 (4.8") (3.94") (1.26")
 With XLR: 600mm (2.36")

Weight: 636g (22.4oz)



'RF Friendly' technology offering immunity from GSM radio frequency interference

Programming options

Program mode (Press number of times for selection required)	Description	Option 1 (Press Once)	Option 2 (Press Twice)
1	Switch Type	Momentary	Latching
2	Switch Action	PTT (Normally Off)	PTM (Normally On)
3	Activation Tone	Off	On
4	Control Mute	On---Microphone muted at base. LED indicates live microphone	Off---Microphone muted externally. LED indicates Logic low
5	Switchable 10dB Pad	0dB	-10dB
6	Bass roll Off	100Hz	400Hz

Switch operating Instructions

- 1) Apply power with switch pressed.
- 2) Unit gives regular flash for 2 seconds on LED to show set up mode entered.
- 3) Press switch the number of times of the programming mode you wish to check or change. The interval between key presses must be less than 1 second.
- 4) After the mode has been selected the LED will flash the number of times of the option currently set.
- 5) Press the switch the number of times of the option required. The interval between key presses must be less than 1 second.
- 6) The LED will flash the number of times of the option already set.
- 7) The unit then returns to stage 2, ready for setting more options.
- 8) The unit will return to normal operation after 5 seconds if the key is not pressed.